arXiv:1303.7054v1 [cs.IT] 28 Mar 2013

Wireless Broadcast with Physical-Layer Network Coding

Shen Feng and Soung C. Liew
Department of Information Engineering
The Chinese University of Hong Kong
{fs010, soung}@ie.cuhk.edu.hk

***Abstract*—This work investigates the maximum broadcast throughput and its achievability in multi-hop wireless networks with half-duplex node constraint. We allow the use of physical-layer network coding (PNC). Although the use of PNC for unicast has been extensively studied, to our best knowledge, there has been little, if any, prior work on PNC for broadcast. Our specific results are as follows: 1) For single-source broadcast, the theoretical throughput upper bound is $n/(n+1)$, where n is the min-cut size of the network. 2) In general, the throughput upper bound is not always achievable. 3) For grid networks, by adopting (n+1)-color partitioning and using PNC, the throughput upper bound $n/(n+1)$ is achievable. Our work can be considered as an attempt to understand the relationship between max-flow and min-cut in half-duplex broadcast networks with cycles (there has been prior work on networks with cycles, but not half-duplex broadcast networks).**

***Index Terms*—Broadcast, wireless networks, throughput, physical-layer network coding.**

I. INTRODUCTION

This work investigates the maximum broadcast throughput and its achievability in multi-hop wireless networks with half-duplex node constraint. It is known that in a single-source unicast network, the max-flow from the source to the sink equals to the min-cut between them. In a single source multicast network, the max-flow is also equal to the min-cut with the adoption of network coding. However, the two results both assume full-duplex links that operate independently without mutual interference. Our work can be considered as an attempt to understand the relationship between max-flow and min-cut in networks with half-duplex links that may interfere with each other, such as those in wireless networks in which the transmission on one link may interfere with transmissions on nearby links, and a node does not transmit and receive at the same time.

We allow the use of physical-layer network coding (PNC) [1]. PNC is a technique that makes possible the utilization of interfering signals. Interference of signals happens when there is more than one stream of electromagnetic wave reach a receiving node at a given time; most of today's wireless networks are designed to avoid interference and interfered signals are usually discarded. Rather than shunning interference, embracing interference and transforming it to network coding operations at the physical layer is the main thrust of PNC. Specifically, when multiple transmitters transmit simultaneously, what is received at the receiver is a superposition of the signals. This superposition can be transformed to network-coded signals for use in a system that exploits network coding.

Although the use of PNC for unicast has been extensively studied, to our best knowledge, there has been little, if any, prior work on PNC for broadcast. Our specific results are as follows:

1) For single-source broadcast, the theoretical throughput upper bound is $n/(n+1)$, where n is the min-cut size of the network.
2) In general, the throughput upper bound is not always achievable.
3) For grid networks, by adopting $(n+1)$-color partitioning and using PNC, the throughput upper bound $n/(n+1)$ is achievable.

The remainder of this paper begins with the introduction of some related works in Section II. In Section III, we analyze the broadcast throughput upper bound in a half-duplex wireless network. Section IV proposes a scheme to achieve this upper bound for grid networks. Finally, section V concludes the results in this work.

II. RELATED WORKS

In graph theory [2], the max-flow min-cut theorem specifies that the maximum throughput in a single-source unicast network is equal to the min-cut. Network coding [3] provides a solution to achieve the upperbound min-cut throughput in a single-source multicast network. Ref. [4] proposed a model for studying the throughput per node of wireless networks. Ref. [5] analyzed the throughput of IEEE 802.11 based ad hoc networks. PNC, first proposed in [1], incorporates signal processing techniques to realize network coding operations at the physical layer when overlapped signals are simultaneously received from multiple transmitters. It is a foundation of our investigation here. Most existing works on PNC focus on the unicast scenario. For example, [1] studied the unicast in a two-way-relay channel, line networks and 2D grid networks; [6] and [7] study the unicast in general networks by designing distributed MAC protocols. As far as we know, there has been little, if any, prior work on broadcast with physical-layer network coding.

III. PNC BROADCAST THROUGHPUT ANALYSIS

We consider the one-source broadcast scenario in which the packets from one source X need to reach all nodes in a packet-based wireless network. Information of these packets needs to be relayed to nodes that are not within the transmission range of X by other nodes.

We represent a packet-based wireless network by an undirected loopless graph $\mathcal{G} = (\mathcal{V}, \mathcal{E})$, where $\mathcal{V}$ is the set of nodes and $\mathcal{E}$ is the set of links. There is a link $\{k, k'\} \in \mathcal{E}$ between two nodes $k, k' \in \mathcal{V}$ if and only if nodes k and k' are within the direct transmission range of each other, i.e., they are within each other's one-hop neighborhood. We assume that each link has equal capacity.

Packets generated and transmitted from X are refered to as "native packets". We assume equal-sized packets and synchronized time-slotted transmissions, in which all nodes are scheduled to transmit at the beginning of a time slot. A time slot is the duration of one packet. A packet x generated and transmitted from X is an element of $GF(2^s)$, where s is the number of bits in the packet. In other words, x is a length-s vector of bits.

Let $\mathcal{N}(k)$ be the set of adjacent nodes of node $k \in \mathcal{V}$. Specifically, $k' \in \mathcal{N}(k)$ if and only if there is a link $\{k, k'\} \in \mathcal{E}$. Each node in our network is half-duplex, i.e., it can either send or receive at a given time, but not both. Whenever a node k transmits, the same information reaches all its adjacent nodes $\mathcal{N}(k)$. We assume that there is no interference from nodes that are two or more hops away and there is no transmission loss or error.[1]

We allow the use of *PNC reception* as defined below.

Definition 1 (PNC Reception). At the physical layer, when a node k receives the superposition of multiple signals containing packets $y_{k'} \in GF(2^s)$ transmitted by several neighbors $k' \in \mathcal{N}(k)$, the node is able to map the composite signal to $z = \bigoplus_{k' \in \mathcal{N}(k)} y_{k'}$. We call z a *PNC packet.*

Readers who are interested in how PNC reception can be realized (with and without channel coding) are referred to [1], [8], [9] for details. We remark that $y_{k'}$ transmitted by each neighbor $k' \in \mathcal{N}(k)$ can be either a native packet or a network-coded packet. The definition of equation/packet is as follows.

Definition 2 (Equation/Packet). An *equation* or a *packet* is expressed as

$$z = \bigoplus_{j} a_j x_j = a_1 x_1 \oplus a_2 x_2 \oplus \ldots, \tag{1}$$

where $a_j, x_j \in GF(2^s)$. It is a linear combination of one or more native packets, where a_j are the coefficients and x_j are the native packets from X. Each of $a_j x_j$ in (1) is an s-bit vector. Similarly, the packet z in (1) is also a s-bit vector. If there are more than one native packet combined in z, then we call it a *network-coded packet.*

In accordance with the addition and multiplication operations in $GF(2^s)$, the addition $\oplus$ in (1) is the bit-wise XOR over $a_j x_j$ for different j, and the multiplication of a_j and x_j for each j in (1) is the multiplication of their polynomial representations modulo an irreducible reducing polynomial.

The terms "packet" and "equation" will be used interchangeably in this paper. A node that has received a packet (i.e., z) also has acquired the associated equation, assuming the coefficients a_j and the identities of the native packets x_j (i.e., the indexes of the native packets) are known. Such index information can be encoded into packet headers. Conceptually, a node will be able to decode D native packets if it has D linearly independent equations (native or network-coded packets) which contains only the D native packets in their summands.

With reference to Definition 1 and Definition 2, for a node k, suppose that a subset of neighbors $\mathcal{N}'(k) \subseteq \mathcal{N}(k)$ transmit simultaneously, and neighbor $k' \in \mathcal{N}'(k)$ transmits $y_{k'} = \bigoplus_{j_{k'}} a_{j_{k'}} x_{j_{k'}}$. Then, PNC reception allows node k to obtain the following equation.

$$z = \bigoplus_{k' \in \mathcal{N}'(k)} y_{k'} = \bigoplus_{k' \in \mathcal{N}'(k)} \left(\bigoplus_{j_{k'}} a_{j_{k'}} x_{j_{k'}} \right) \tag{2}$$

Note that node k' that transmits $y_{k'} = \bigoplus_{j_{k'}} a_{j_{k'}} x_{j_{k'}}$ may perform upper-layer network coding to obtain $y_{k'} = \bigoplus_{j_{k'}} a_{j_{k'}} x_{j_{k'}}$ from the data that it has received so far. That is, in (2) above, $y_{k'}$ is a packet or network-coded packet generated by upper-layer network coding at a transmitting node; whereas z is a physical-layer network-coded packet generated at the receiving node based on the simultaneous signals received from multiple transmitting source. In this paper, we will be using PNC as well as upper-layer network coding to enable efficient broadcasting.

Definition 3 (Trivial Network). Consider a network $\mathcal{G} = (\mathcal{V}, \mathcal{E})$. If all nodes in the network are neighbors of X (i.e., $\mathcal{N}(X) = \mathcal{V} \backslash \{X\}$), then the network is called a *trivial network.*

In a trivial network, all non-source nodes can receive directly from X. Relaying information from a node to the other is thus unnecessary. There is little value to consider trivial networks in our analysis, as the optimal strategy of transmission/reception is trivial, i.e., X transmits all the time, and the normalized broadcast throughput is 1. In this paper, we are only interested in non-trivial networks.

Consider a cut $C = (\mathcal{V}_1, \mathcal{V}_2)$ in a network $\mathcal{G} = (\mathcal{V}, \mathcal{E})$ that partitions the nodes $\mathcal{V}$ in into two subsets $\mathcal{V}_1$and $\mathcal{V}_2$. Let $\mathcal{V}_1$ be the subset that contains X. Let $\mathcal{V}_1' \subseteq \mathcal{V}_1$ be nodes in $\mathcal{V}_1$ that has neighbors in $\mathcal{V}_2$, and $\mathcal{V}_2' \subseteq \mathcal{V}_2$ to be nodes in $\mathcal{V}_2$ that has neighbors in $\mathcal{V}_1$. That is, the nodes in $\mathcal{V}_1 \backslash \mathcal{V}_1'$ and the nodes in $\mathcal{V}_2 \backslash \mathcal{V}_2'$ are not connected. The information from X has to go through some nodes in $\mathcal{V}_1'$ in order to reach nodes in $\mathcal{V}_2$. .

Definition 4 (Vertex-Cut Size). Consider a cut C. Let $\mathcal{V}_1, \mathcal{V}_2, \mathcal{V}_1'$ and $\mathcal{V}_2'$ be define as above. The *vertex-cut size* of C is $|\mathcal{V}_1'|$.

---

[1] This assumption is made to simplify the analysis. In practice, we could either employ a forward error control (FEC) scheme or an automatic-repeat-request (ARQ) scheme to ensure reliable communication. Both incur some overhead in the amount of data to be transmitted. For PNC broadcast, FEC is perhaps simpler in that acknowledgements from multiple receivers may complicate the ARQ design.



Fig. 1: Partitioning with a qualified cut

Note the difference between the definition of the traditional cut size and the above vertex-cut size. The traditional cut size is defined to be the number of edges from nodes in $\mathcal{V}_1'$ to nodes in $\mathcal{V}_2'$. The motivation for the above vertex-cut size is due to the wireless node constraint we assume: specifically, a node cannot transmit different information on different links incident to it; when it transmits, it broadcasts the same information on all these links. Thus, the vertex-cut size better characterizes the maximum flow that can go from $\mathcal{V}_1$ to $\mathcal{V}_2$.

Definition 5 (Qualified Cut). Consider a cut $C = (\mathcal{V}_1, \mathcal{V}_2)$. Let $\mathcal{V}_1, \mathcal{V}_2, \mathcal{V}_1'$ and $\mathcal{V}_2'$ be defined as above. C is said to be a *qualified cut* if and only if $X \notin \mathcal{V}_1'$.

Fig. 1 shows the partitioning with a qualified cut. A qualified cut ensures the adjacent nodes of X are in the same sub-network, $\mathcal{V}_1$, as X. A qualified cut does not exist in a trivial network, and can always be found in a non-trivial networks. Intuitively, the broadcast throughput from X to all other nodes is limited by the need to relay information to nodes that are not direct neighbors of source X. Thus, the throughput limit should be characterized by the qualified cut in that it characterizes the "relay capacity" to nodes that are two or more hops away from X.

In this paper, we consider the problem of source X broadcasting D native packets to all other nodes in the network for large D. Let W_D be the number of time slots (or time window) before all nodes acquire all the D native packets. The D native packets can be obtained if a node has received D linearly independent equations relating the D native packets.

Definition 6 (Throughput). The broadcast *throughput* ρ of source X is $\lim_{D\to\infty} D/W_D$.

Each qualified cut has an associated vertex-cut size. The qualified cuts with the minimum vertex-cut size in the network are called the *minimum qualified cuts*. The following theorem gives an upper bound on the achievable broadcast throughput:

Theorem 1. *Consider a non-trivial network $\mathcal{G}$ whose minimum qualified cuts have vertex-cut size n. Then $\rho \le n/(n+1)$.*

Proof of Theorem 1: With respect to Definition 5, let C be a minimum qualified cut with vertex-cut size n. Suppose the D packets to be broadcast by X are $\{x(0), ..., x(D-1)\}$. There are two ways to deliver information related to these D native packets from nodes in $\mathcal{V}_1'$ to nodes in $\mathcal{V}_2'$:
1) deliver the information directly in the original form of the D native packets; or
2) deliver at least D linearly independent equations (native or network-coded packets) with $x(0), ..., x(D-1)$ as unknowns.
Either way, there must be at least D transmissions (taking up D time slots) from nodes in $\mathcal{V}_1'$ to nodes in $\mathcal{V}_2'$.

Recall that W_D is the total number of time slots needed for all nodes to receive D linearly independent equations relating the D native packets. We label the nodes in $\mathcal{V}_1'$ by $1, 2, ..., n$ (see Fig. 1). Let $T_1, T_2, ..., T_n$ be the numbers of packets transmitted by nodes $1, 2, ..., n$, respectively, by the end of W_D time slots. Let $R_1, R_2, ..., R_n$ be the numbers of packets received by nodes $1, 2, ..., n$, respectively, by the end of W_D time slots. Then with the half-duplex constraint (nodes cannot transmit and receive at the same time),

$$W_D = T_i + R_i \text{ for all nodes } i, 1 \le i \le n. \tag{3}$$

Furthermore, since each node $i, 1 \le i \le n$, must be able to decode the D packets from the receptions (i.e., it must have received at least D linearly independent equations), we have

$$R_i \ge D \tag{4}$$

for all $1 \le i \le n$. In addition, at least D linearly independent equations must be delivered to nodes in $\mathcal{V}_2'$ from nodes in $\mathcal{V}_1'$, meaning

$$T_1 + T_2 + ... + T_n \ge D. \tag{5}$$

Thus, the network throughput is

$$\rho = \lim_{D\to\infty} \frac{D}{W_D} = \lim_{D\to\infty} \frac{D}{T_i + R_i} \le \lim_{D\to\infty} \frac{D}{T_i + D}. \tag{6}$$

Note that $T_1, T_2, ..., T_n$ and $R_1, R_2, ..., R_n$ (i.e., how many times each node transmits and how many times each node receives) depend on the detailed scheduling and relaying scheme. Here, we are interested in an upper bound that is valid for all schemes, including the optimal scheduling scheme. To do so, we can solve the following optimization problem:

$$\max \min_{1\le i\le n} \lim_{D\to\infty} \frac{D}{T_i + D} \tag{7}$$

such that

$$T_1 + T_2 + ... + T_n \ge D.$$

As $D \to \infty$, the solution to the above problem is

$$T_i = \frac{D}{n}, \forall 1 \le i \le n. \tag{8}$$

The upper bound of ρ is therefore

$$\rho \le \lim_{D\to\infty} \frac{D}{\frac{D}{n} + D} = \frac{n}{n+1} \tag{9}$$

■

The upper bound of broadcast throughput is not always achievable. For example, the minimum qualified cut in the network shown in Fig. 2 has vertex-cut size 2. However, a throughput of 2/3 cannot be achieved. The reader is referred to the Appendix for details.



Fig. 2: Example of a network whose broadcast throughput cannot reach the upper bound $n/(n+1)$

Although not always achievable in general, the throughput upper bound $n/(n+1)$ is achievable in grid networks. The next section shows how it can be achieved.

IV. BROADCAST SCHEME FOR GRID NETWORKS

We now argue that throughput of $n/(n+1)$, where n is the min qualified cut size, in grid networks. In grid networks, $n = 2$. To demonstrate its achievability, we have to come up with a scheduling scheme specifying for each and every node, (i) the time slots during which it transmits; and (ii) the information it will transmit during its transmission time slots.

For the scheduling scheme we will construct, the time slots are divided into three disjoint groups (colors) of equal size. Each node is assigned one of the three colors. For that the source node X, each non-source node can only transmit during the time slots of its color.

We first review the concept of Hamiltonian cycle and present a scheme to color the nodes in a grid network based on an embedded Hamiltonian cycle. The coloring in turn helps us construct the transmission schedules of the nodes.

A. *Coloring of networks by constructing Hamiltonian cycles*

A Hamiltonian cycle is a path that visits each node in a graph exactly once and ends at its starting point. First, for any $M \times N$ grid graph with at least one of M, N being even, there is a Hamiltonian cycle in the graph [2]. For example, we can construct a comb-shaped Hamiltonian cycle as shown in Fig. 3a. Starting from a neighbor of X on the cycle, we number along the path by 1-2-3-...-(MN-1). Depicted in Fig. 3b is an example of this numbering scheme in a 6×5 grid with $X = (1, 1)$.

Next, if M and N are both odd, then it is not possible to construct a Hamiltonian cycle in the grid [2]. Instead, we construct a pseudo Hamiltonian cycle called the "Split-Merge Hamiltonian cycle", as illustrated in Fig. 4a and 4b. As shown in Fig. 4b, after visiting node 5, the visits split into two paths. Nodes 6 and 6* are visited in parallel next; node 7 and 7* after that; an then node 8 and 8*; finally the parallel visits merge back to node 9. By splitting and merging as such, a result is the insertion of a new row (as indicated red in Fig. 4b) into an $(M-1) \times N$ network which already has a Hamiltonian cycle constructed (because $M-1$ is even, we can construct such a cycle).



(a) A Hamiltonian cycle in an $M \times N$ network (M is even).

(b) Numbering of nodes in a 6×5 network after renumbering.

Fig. 3: $M \times N$ networks with at least one of M, N being even



(a) A Hamiltonian cycle, part of whom is a parallel path, in an $M \times N$ network (M and N are both odd).

(b) Numbering of nodes in a 7×5 network.

Fig. 4: $M \times N$ networks with both M, N being odd

Hamiltonian Node Coloring: Now that we have a numbering scheme for all grid networks, we *partition the non-source nodes into nodes of three distinct colors* $c \in \{0, 1, 2\}$. We assign a node with number k the color $c = k \bmod 3$. We also let $k^* \bmod 3 := k \bmod 3$, i.e., let the node k^* in the split paths have the same color as node k.

The motivation of the coloring scheme based on the Hamiltonian cycle is as follows. A node k that is two or more hops away from X can only receive the broadcast information from X through its neighbors $\mathcal{N}(k)$. In our time-slotted scheme to be described, the nodes with the same color transmit at the same time. The Hamiltonian coloring scheme ensures that each node k has at least two neighbors assigned with the two colors different from the color of node k. These two other colors correspond to the time slots in which node k receives. Thus, each node k receives in at least two time slots out of every three time slots. Section IV-B specifies this transmission scheme more exactly.

B. *Ternary transmission schedule*

Definition 7 (Round). A *round* $t, t = 0, 1, 2, ...$ is a set of three time slots $\{3t, 3t+1, 3t+2\}$.

Our basic idea is to let nodes with color c transmit in time slots $3t+c, t=0,1,2...$ As a consequence, every node transmits once and receives twice in every round.

If we could ensure that in each round, every node receives two packets that contain new information, then the broadcast throughput would be $2/3$, which is the upper bound given by Theorem 1. Toward that end, we propose a schedule with the following rules (also summarized in Table I):

1) Let the sequence of native packets to be broadcast by X be $\{x_0(t)\}_{t=0,1,2,..}$ and $\{x_1(t)\}_{t=0,1,2,...}$.
2) In time slot $3t$, X transmits $x_0(t)$; in time slot $3t+1$, X transmits $x_1(t)$; in time slot $3t+2$, X transmits $x_0(t) \oplus x_1(t)$.
3) This rule describes the behavior of a node that is not adjacent to X:
   In time slot $3t+c, c \in \{0,1,2\}$, node k, $k \notin \mathcal{N}(X)$, with color c transmits
   $$y^k(t) = \alpha_k(z_0^k(t) \oplus z_1^k(t)),$$
   where $\alpha_k \in GF(2^s)\backslash\{0\}$ is a coefficient, and
   $$z_0^k(t) = r_0^k(t-1) - \bigoplus_{\substack{l: l\in\mathcal{N}(k), l \bmod 3=(c-1) \bmod 3,\\ l\neq 1 \text{ or } MN-1}} \alpha_l y^k(t-2)$$
   $$z_1^k(t) = r_1^k(t-1) - \bigoplus_{\substack{l: l\in\mathcal{N}(k), l \bmod 3=(c+1) \bmod 3,\\ l\neq 1 \text{ or } MN-1}} \alpha_l y^k(t-2).$$
   In the above, $r_0^k(t-1), r_1^k(t-1)$ are the two packets node k receives from its neighbors in the previous round in time slots $3t-3+((c-1) \bmod 3)$ and $3t-3+((c+1) \bmod 3)$. (note that these two time slots are the two time slots with different colors than c). In the above equation, by subtracting $\alpha_l y^k(t-2)$, we subtract out the information node k sent to an adjacent node l two rounds earlier, who now sends back $y^k(t-2)$ multiplied by its coefficient α_l. This prevents the same information from looping back and forth between the node and its adjacent nodes.
4) This rule describes the behavior of node 1 and node (MN-1):
   Node 1 and node (MN-1) only transmit native packets times a coefficient. Specifically, node 1 transmits $x_0(t-1)$ in time slot $3t+1$. Node (MN-1) transmits $x_1(t-1)$ in time slot $3t+c$, where $c=(MN-1) \bmod 3$ is its color. We refer to these two nodes as "*virtual sources*". Node 1 and node (MN-1) are responsible for forwarding $\{x_0(t)\}_{t=0,1,2,..}$ and $\{x_1(t)\}_{t=0,1,2,..}$, respectively. Henceforth, let node 1 be denoted by X_0 and node (MN-1) be denoted by X_1. We show below that being adjacent to X, they can both derive $x_0(t-1)$ and $x_1(t-1)$ by the end of round $t-1$.
   In the three time slots in round $t-1$, source X transmits $x_0(t-1)$, $x_1(t-1)$, and $x_0(t-1) \oplus x_1(t-1)$ respectively. Since each adjacent node of X is colored with one color only, it is in receiving mode in two of the three time slots. Both $x_0(t-1)$ and $x_1(t-1)$ can be derived based on the receptions in these two time slots.



(a) Equivalent of a 6×5 network (b) Equivalent of a 7×5 network

Fig. 5: Equivalent networks after removing X



(a) Numbering (b) Coloring

Fig. 6: A 2×3 network example

5) This rule describes the behavior of adjacent nodes of X who are not the the virtual sources, X_0 and X_1. By this rule, we ensure that only the two virtual sources can send out the newest native packets of X:
   An adjacent node k of X, who is not X_0 or X_1, can also derive $x_0(t-1)$ and $x_1(t-1)$ by the end of round $t-1$. In round t, node k transmits
   $$y^k(t) = \alpha_k(\tilde{z}_0^k(t) \oplus \tilde{z}_1^k(t)),$$
   where $\alpha_k \in GF(2^s)\backslash\{0\}$ is a coefficient, and
   $$\tilde{z}_0^k(t) = z_0^k(t) - x_0'(t-1)$$
   $$\tilde{z}_1^k(t) = z_1^k(t) - x_1'(t-1).$$
   In the above, $z_0^k(t), z_1^k(t)$ are defined as in rule 3, and $x_0'(t-1)$ and $x_1'(t-1)$ are the two packets sent by X and received by this node in round $t-1$.
   For example, if anode k has color 0, then $x_0'(t-1)$ and $x_1'(t-1)$ are the two packets sent by X in time slots $3t-1$ and $3t-2$, respectively; i.e., $x_0'(t-1) = x_0(t-1) \oplus x_1(t-1)$ and $x_1'(t-1) = x_1(t-1)$.

Transformation to Two-Source Broadcast Problem: With the above rules, only the virtual sources X_0 and X_1 can be considered as the origins of the newest information. The single-source networks in Fig. 3b and Fig. 4b can then be transformed to two-source networks in Fig. 5a and Fig. 5b. In Fig. 5a, nodes 1 and 29 are X_0 and X_1, respectively; in Fig. 5b, nodes 1 and 31 are X_0 and X_1, respectively.

Example

We first illustrate what happens when applying this schedule to a simple 2×3 grid network. The source is located at (0,0). Fig. 6a shows the numbering of this network and Fig. 6b shows the corresponding coloring. In this example, we

ts (time slot)	Node X	X_0 (Node 1)	X_1 (Node $MN-1$)	Color-0 nodes	Color-1 nodes	Color-2 nodes
$3t$	$x_0(t)$	-	$x_1(t-1)$ if $(MN-1) \bmod 3 = 0$; nothing otherwise	$\alpha_k(z_0^k(t) \oplus z_1^k(t))$	-	-
$3t+1$	$x_1(t)$	$x_0(t-1)$	$x_1(t-1)$ if $(MN-1) \bmod 3 = 1$; nothing otherwise	-	$\alpha_k(z_0^k(t) \oplus z_1^k(t))$	-
$3t+2$	$x_0(t) \oplus x_1(t)$	-	$x_1(t-1)$ if $(MN-1) \bmod 3 = 2$; nothing otherwise	-	-	$\alpha_k(z_0^k(t) \oplus z_1^k(t))$

TABLE I: Ternary transmission schedule

t	*ts*	Node X	Node 1	Node 2	Node 3	Node 4	Node 5
0	0	s:$x_0(0)$	r:$x_0(0)$	-	-	-	r:$x_0(0)$
	1	s:$x_1(0)$	r:$x_1(0)$	-	-	-	r:$x_1(0)$
	2	s:$x_0(0) \oplus x_1(0)$	-	-	-	-	-
1	3	s:$x_0(1)$	r:$x_0(1)$	-	-	-	r:$x_0(1)$
	4	s:$x_1(1)$	s:$x_0(0)$	r:$x_0(0)$	-	-	r:$x_1(1)$
	5	s:$x_0(1) \oplus x_1(1)$	r:$x_0(1) \oplus x_1(1)$ d:$x_1(1)$	-	-	r:$x_1(0)$	s:$x_1(0)$
2	6	s:$x_0(2)$	r:$x_0(2)$	-	-	-	r:$x_0(2)$
	7	s:$x_1(2)$	s:$x_0(1)$	r:$x_0(1)$	r:$x_1(0)$	s:$x_1(0)$	r:$x_1(2) \oplus x_1(0)$ d:$x_1(2)$
	8	s:$x_0(2) \oplus x_1(2)$	r:$x_0(2) \oplus x_1(2) \oplus x_0(0)$ d:$x_1(2)$	s:$x_0(0)$	r:$x_0(0)$	r:$x_1(1)$	s:$x_1(1)$
3	9	s:$x_0(3)$	r:$x_0(3)$	r:$x_0(0) \oplus x_1(0)$ d:$x_1(0)$	s:$x_0(0) \oplus x_1(0)$	r:$x_0(0) \oplus x_1(0)$ d:$x_0(0)$	r:$x_0(3)$
	10	s:$x_1(3)$	s:$x_0(2)$	r:$x_0(2)$	r:$x_1(1)$	s:$x_1(1)$	r:$x_1(3) \oplus x_1(1)$ d:$x_1(3)$
	11	s:$x_0(3) \oplus x_1(3)$	r:$x_0(3) \oplus x_1(3) \oplus x_0(1)$ d:$x_1(3)$	s:$x_0(1)$	r:$x_0(1)$	r:$x_1(2)$	s:$x_1(2)$
4	12	s:$x_0(4)$	r:$x_0(4)$	r:$x_0(1) \oplus x_1(1)$ d:$x_1(1)$	s:$x_0(1) \oplus x_1(1)$	r:$x_0(1) \oplus x_1(1)$ d:$x_0(1)$	r:$x_0(4)$
	13	s:$x_1(4)$	s:$x_0(3)$	r:$x_0(3)$	r:$x_0(0) \oplus x_1(2)$ d:$x_1(2)$	s:$x_0(0) \oplus x_1(2)$	r:$x_1(4) \oplus x_0(0) \oplus x_1(0) \oplus x_1(2)$ d:$x_1(4)$
	14	s:$x_0(4) \oplus x_1(4)$	r:$x_0(4) \oplus x_1(4) \oplus x_0(2) \oplus x_1(0)$ d:$x_1(4)$	s:$x_0(2) \oplus x_1(0)$	r:$x_0(2) \oplus x_1(0)$ d:$x_0(2)$	r:$x_1(3)$	s:$x_1(3)$

TABLE II: Ternary transmission schedule for a 2×3 network. "s", "r" and "d" indicate "send", "receive" and "derive", respectively.

set all coefficients α_k to 1. The transmissions of our ternary schedule are shown in Table II. Although node 1 and node 4 can overhear each other, they are of the same color and thus transmit at the same time. Hence they will not interfere each other. Note that in time slot 9, node 3 transmits $x_0(0) \oplus x_1(0)$. Upon receiving $x_0(0) \oplus x_1(0)$, node 2 can decode $x_1(0)$ because it already has $x_0(0)$; node 4 can decode $x_0(0)$ because it has $x_1(0)$. From round 3 onwards, every non-source node receives sufficient information for it to derive two new native packets in each round. Thus, the throughput is $2/3$.

It can be observed that the two virtual sources node 1 and node 5 always have $x_0(0), ..., x_0(t)$ and $x_1(0), ..., x_1(t)$ by the end of round t. Therefore they can always derive $x_0(t+1)$ and $x_1(t+1)$ by the end of round $t+1$ even if they receive PNC packets during round $t+1$, because they know all but one of the unknowns (native packets).

In this example each node can obtain two native packets in a round. In a general network where there is interference among nodes, obtaining native packets cannot be guaranteed. However, as will be shown, we could ensure every non-source node still obtains two linearly independent equations in each round.

In a general grid network, depending on its position in the grid, a node can have up to four neighbors. With the Hamiltonian Node Coloring, it is possible for a node to have two or three neighbors of the same color, only one of which is the adjacent node on the Hamiltonian cycle (see Section IV-A on Hamiltonian Node Coloring). When multiple neighbors of the same color transmit simultaneously, the node receive a PNC packet, for which the XOR of the simultaneous transmissions of the neighbors of the same color is received. For example, in Fig. 4b, node 9 (color-0) has four neighbors: node 8 (color-2), node 8* (color-2), node 10 (color-1) and node 20 (color-2). As a consequence, in each round node 9 receives from three nodes simultaneously in the color-2 time slot, which yields a PNC packet; it receives from only one neighbor in the color-1 time slot. For both packets, we need to make sure:

1) the packet received is linearly independent with all packets previously received;
2) the packet received is not null.

C. Random Coefficients

In the previous simple 2×3 example, the coefficients α_k for all nodes k, $k \neq 1$ or $MN-1$, were set to 1. In a general grid, this scheme may not work. Henceforth, we consider a time-varying random coefficient scheme. Specifically, the coefficient $\alpha_k(t)$ of node k in round t is chosen uniformly randomly from the non-zero element of $GF(2^s)$, and $\alpha_k(t)$ for different k and t are i.i.d. The sequences of packets $x_0(t)_{t=0,1,2,...}$ and $x_1(t)_{t=0,1,2,...}$ transmitted by the virtual sources X_0 and X_1 remain the same, and their coefficients can be considered as 1 throughout the process. We show that with high probability, things will work out so that the grid network will have throughput of $2/3$.

In grid networks, the newest information (i.e., signals embedded with the latest native packets) could come through a shortest path from the the virtual sources X_0 and X_1 rather than through the sequence of nodes along the Hamiltonian cycle.

Definition 8 (**Shortest Path**). A *shortest path* from a virtual source to a node is a shortest sequence of adjacent nodes leading from the virtual source to the node, in which no two adjacent nodes in the sequence are of the same color.

Note that in general there could be multiple shortest paths of the same length leading from a virtual source to a node, and some of them may share some common intermediate nodes.

Definition 9 (**Hamiltonian Sub-paths**). The paths from the virtual sources X_0 (numbered 1) and X_1 (numbered $MN-1$) to a node k along the Hamiltonian cycle, i.e., $p_0 = 1 - 2 - ... - k$ and $p_1 = (MN-1) - (MN-2) - ... - k$, are called *Hamiltonian sub-paths* of node k.

Definition 10 (**Coefficient Product of a Path**). The *coefficient product* of $p = k_1 - k_2 - ... - k_l - k$, a path from node k_1 to node k, in round t is

$$\begin{aligned} g_p(t) =& \alpha_{k_1}(t-(l-1))\alpha_{k_2}(t-(l-2)) \\ & ...\alpha_{k_{l-1}}(t-1)\alpha_{k_l}(t) \qquad (10) \\ =& \prod_{r=1}^{l} \alpha_{k_r}(t-(l-r)), \qquad (11) \end{aligned}$$

where $\alpha_{k_1}(t-(l-1)), \alpha_{k_2}(t-(l-2), ..., \alpha_{k_{l-1}}(t-1), \alpha_{k_l}(t)$ are the coefficients of nodes $k_1, k_2, ..., k_{l-1}, k_l$ in rounds $t-(l-1), t-(l-2), ..., t-1, t$, respectively.

If a native packet x goes through a path p, then its coefficient when it arrives at the last node will be $g_p(t)$, the coefficient product of this path. If a native packet begins its journey from a node j with an initial coefficient α_j and arrives at a node k in the same time slot in round t via multiple paths $p_1, p_2, ...$, then the coefficient of the native packet x when it is received at node k is the sum of coefficient products $\alpha_j g_{p_1}(t) \oplus \alpha_j g_{p_2}(t) \oplus ...$ Note that these multiple paths must have the same number of hops since different copies of packet x are supposed to arrive at node k together in the same time slot.

Lemma 1. *The coefficient product $g_p(t)$ of a path $p = k_1 - k_2 - ... - k_l - k$ is non-zero for $t \geq l-1$, and is uniformly randomly distributed over in $GF(2^s)\backslash\{0\}$.*

Proof of Lemma 1: Since $\alpha_{k_1}(t-(l-1)), \alpha_{k_2}(t-(l-2), ..., \alpha_{k_{l-1}}(t-1), \alpha_{k_l}(t)$ are i.i.d. uniformly distributed over $GF(2^s)\backslash\{0\}$ when $t \geq l-1$, $g_p(t) = \prod_{r=1}^{l} \alpha_{k_r}(t-(l-r))$ is non-zero and is uniformly distributed over $GF(2^s)\backslash\{0\}$. ■

Example of received packets

For example in Fig. 4b, in time slot $3t$, node 10 receives from node 9. The shortest path from X_0 to node 10 is $p_0 = 1 - 8 - 9 - 10$. However, this is the shortest path for $\{x_0(t)\}_{t=0,1,...}$, because node 1 only transmits $\{\alpha_1(t)x_0(t)\}_{t=0,1,...}$. Shortest paths from X_1 to node 10 for $\{x_1(t)\}_{t=0,1,...}$ are $p_1 = 31 - 2 - 1 - 8 - 9 - 10$, $p_2 = 31 - 2 - 7 - 8 - 9 - 10$ and $p_3 = 31 - 2 - 7 - 8^* - 9 - 10$. A native packet in $\{x_0(t)\}_{t=0,1,...}$ will be multiplied by the coefficient of the sender when being sent. The packet node 10 receives from node 9 in time slot $3t$ is

$$\begin{aligned} r_0^{10}(t) =& g_{p_0}(t)x_0(t-3) \\ & \oplus (g_{p_1}(t) \oplus g_{p_2}(t) \oplus g_{p_3}(t))x_1(t-5) \\ & \oplus f(x_0(t-4), x_0(t-5), ..., x_0(0)) \\ & \oplus f(x_1(t-6), x_1(t-7), ..., x_1(0)) \qquad (12) \\ =& \alpha_1(t-2)\alpha_8(t-1)\alpha_9(t)x_0(t-3) \\ & \oplus (\alpha_{31}(t-4)\alpha_2(t-3)\alpha_1(t-2)\alpha_8(t-1)\alpha_9(t) \\ & \oplus \alpha_{31}(t-4)\alpha_2(t-3)\alpha_7(t-2)\alpha_8(t-1)\alpha_9(t) \\ & \oplus \alpha_{31}(t-4)\alpha_2(t-3)\alpha_7(t-2)\alpha_{8^*}(t-1)\alpha_9(t)) \\ & x_1(t-5) \\ & \oplus f(x_0(t-4), x_0(t-5), ..., x_0(0)) \\ & \oplus f(x_1(t-6), x_1(t-7), ..., x_1(0)) \qquad (13) \end{aligned}$$

where $f(\cdot)$ is a linear combination of the arguments.

The time indexes of the newest native packets in Eqn. (13) escalate over time. Therefore each new $r_0^{10}(t)$ is linearly independent with all $r_0^{10}(t'), t' < t$.

$r_1^{10}(t)$, the packet node 10 receives in time slot $3t+2$ will be a PNC packet from nodes 11 and 17. A shortest path in this time slot for $\{x_0(t)\}_{t=0,1,...}$ is $1-8-21-20-19-18-17-10$; and a shortest path for $\{x_1(t)\}_{t=0,1,2,...}$ is $31-2-7-8^*-7^*-12-11-10$. Therefore the newest native packets in it would be $x_0(t-7)$ and $x_1(t-7)$, multiplied by some $\bigoplus_{p \in S} g_p(t)$, where S is the set of all shortest paths and p is a shortest path for the native packet.

Packets received by a general node

Consider a general node $k, k \neq 1$ or $MN-1$, in the network. Focus on one of its two receiving time slots in round t. Let S_0, S_1 be the sets of shortest paths for $\{x_0(t)\}_{t=0,1,...}$ and $\{x_1(t)\}_{t=0,1,...}$, respectively, in this time slot; and S_0^{+q}, S_1^{+q} be the sets of paths that are q hops longer than S_0 and S_1 for $\{x_0(t)\}_{t=0,1,...}$ and $\{x_1(t)\}_{t=0,1,...}$, respectively. Depending on q, each of S_0^{+q} and S_1^{+q} may or may not be empty. For example when $q < 0$, both S_0^{+q} and S_1^{+q} will be empty and thus $a_{S_0^{+q}}(t) = 0$ and $a_{S_1^{+q}}(t) = 0$.

In round t, node k receives

$$\begin{aligned} z_0(t) =& a_{S_0}(t)x_0(t-i_0) \oplus a_{S_0^{+1}}(t)x_0(t-i_0-1) \\ & \oplus ... \oplus a_{S_0^{+t-i_0}}(t)x_0(0) \\ & \oplus a_{S_1}(t)x_1(t-i_1) \oplus a_{S_1^{+1}}(t)x_1(t-i_1-1) \\ & \oplus ... \oplus a_{S_1^{+t-i_1}}(t)x_1(0), \qquad (14) \end{aligned}$$

where i_0 and i_1 are the lengths of paths in S_0 and S_1, respectively; and

$$a_{S_0}(t) = \bigoplus_{p \in S_0} g_p(t), \; a_{S_1}(t) = \bigoplus_{p \in S_1} g_p(t), \qquad (15)$$

$$a_{S_0^{+q}}(t) = \bigoplus_{p \in S_0^{+q}} g_p(t),\ a_{S_1^{+q}}(t) = \bigoplus_{p \in S_1^{+q}} g_p(t). \tag{16}$$

Grouping the packets received in this colored slot in all rounds, we have a linear equation system $\{z_0(t)\}_{t \geq \min(i_0, i_1)}$.

Now consider the other receiving time slot of node k in round t. Let T_0, T_1 be the sets of shortest paths for $\{x_0(t)\}_{t=0,1,...}$ and $\{x_1(t)\}_{t=0,1,...}$, respectively, in this time slot; and T_0^{+q}, T_1^{+q} be the sets of paths that are q hops longer than T_0 and T_1 for $\{x_0(t)\}_{t=0,1,...}$ and $\{x_1(t)\}_{t=0,1,...}$, respectively. Node k receives

$$\begin{aligned} z_1(t) =& a_{T_0}(t)x_0(t-j_0) \oplus a_{T_0^{+1}}(t)x_0(t-j_0-1) \\ & \oplus ... \oplus a_{T_0^{+t-j_0}}(t)x_0(0) \\ & \oplus a_{T_1}(t)x_1(t-j_1) \oplus a_{T_1^{+1}}(t)x_1(t-j_1-1) \\ & \oplus ... \oplus a_{T_1^{+t-j_1}}(t)x_1(0), \end{aligned} \tag{17}$$

where j_0 and j_1 are the lengths of paths in T_0 and T_1, respectively; and

$$a_{T_0}(t) = \bigoplus_{p \in T_0} g_p(t),\ a_{T_1}(t) = \bigoplus_{p \in T_1} g_p(t), \tag{18}$$

$$a_{T_0^{+q}}(t) = \bigoplus_{p \in T_0^{+q}} g_p(t),\ a_{T_1^{+q}}(t) = \bigoplus_{p \in T_1^{+q}} g_p(t). \tag{19}$$

Grouping the packets received in this colored slot in all rounds, we have another linear equation system$\{z_1(t)\}_{t \geq \min(j_0, j_1)}$.

For simplicity, we assume the number of native packets from the source X is an even number $2D$, where D is an integer. Hence there are D native packets from each of the virtual sources X_0 and X_1. As a consequence, $\{x_0(t)\}_{t=0,1,...} = \{x_0(t)\}_{t=0,1,...,D-1}$ and $\{x_1(t)\}_{t=0,1,...} = \{x_1(t)\}_{t=0,1,...,D-1}$. After all native packets have been sent by the source, we allow MN more time slots for them to circulate in the network. During these MN time slots, the source and the virtual sources can be considered as transmitting null packets, which do not increase the number of unknowns in the network. For node $k, 1 < k < MN-1$, let

$$k' = MN - k. \tag{20}$$

We select $\{z_0(t_0)\}_{k-1 \leq t_0 \leq D+k-2}$, a subset of $\{z_0(t)\}_{t \geq \min(i_0,i_1)}$, and $\{z_1(t_1)\}_{k'-1 \leq t_1 \leq D+k'-2}$, a subset of $\{z_1(t)\}_{t \geq \min(j_0,j_1)}$, and group them together as a single linear equation system

$$\{z_0(t_0), z_1(t_1)\}_{k-1 \leq t_0 \leq D+k-2, k'-1 \leq t_1 \leq D+k'-2}. \tag{21}$$

If all equations in (21) are linearly independent, then we can derive all $2D$ native packets from (21). For this purpose, we represent (21) in matrix form as follows:

$$A(D-1)\mathbf{x} = \mathbf{z}(D-1), \tag{22}$$

where

$$A(D-1) = \begin{bmatrix} \mathbf{u_0}(k-1) & \mathbf{u_1}(k-1) \\ \vdots & \vdots \\ \mathbf{u_0}(D+k-2) & \mathbf{u_1}(D+k-2) \\ \mathbf{v_0}(k'-1) & \mathbf{v_1}(k'-1) \\ \vdots & \vdots \\ \mathbf{v_0}(D+k'-2) & \mathbf{v_1}(D+k'-2) \end{bmatrix} \tag{23}$$

$$\mathbf{x} = \begin{bmatrix} x_0(0) \\ \vdots \\ x_0(D-1) \\ x_1(0) \\ \vdots \\ x_1(D-1) \end{bmatrix} \mathbf{z}(D-1) = \begin{bmatrix} z_0(k-1) \\ \vdots \\ z_0(D+k-2) \\ z_1(k'-1) \\ \vdots \\ z_1(D+k'-2) \end{bmatrix}. \tag{24}$$

In $A(D-1)$, $\mathbf{u_0}(t), \mathbf{u_1}(t), \mathbf{v_0}(t), \mathbf{v_1}(t)$ are defined as follows:

$$\mathbf{u_0}(t) = \begin{bmatrix} a_{S_0^{+t-i_0}}(t) \\ a_{S_0^{+t-1-i_0}}(t) \\ \vdots \\ a_{S_0^{+0}}(t) \\ 0 \\ \vdots \\ 0 \end{bmatrix}^T \mathbf{u_1}(t) = \begin{bmatrix} a_{S_1^{+t-i_1}}(t) \\ a_{S_1^{+t-1-i_1}}(t) \\ \vdots \\ a_{S_1^{+0}}(t) \\ 0 \\ \vdots \\ 0 \end{bmatrix}^T \tag{25}$$

$$\mathbf{v_0}(t) = \begin{bmatrix} a_{T_0^{+t-j_0}}(t) \\ a_{T_0^{+t-1-j_0}}(t) \\ \vdots \\ a_{T_0^{+0}}(t) \\ 0 \\ \vdots \\ 0 \end{bmatrix}^T \mathbf{v_1}(t) = \begin{bmatrix} a_{T_1^{+t-j_1}}(t) \\ a_{T_1^{+t-1-j_1}}(t) \\ \vdots \\ a_{T_1^{+0}}(t) \\ 0 \\ \vdots \\ 0 \end{bmatrix}^T \tag{26}$$

Note that by definition $S_0^{+0}, S_1^{+0}, T_0^{+0}, T_1^{+0}$ are the shortest paths S_0, S_1, T_0, T_1, and i_0, i_1, j_0, j_1 are the lengths of paths in S_0, S_1, T_0, T_1, respectively (defined in (14) and (17)). There are $\max(0, D-t+i_0-1)$,$\max(0, D-t+i_1-1)$, $\max(0, D-t+j_0-1)$ and $\max(0, D-t+j_1-1)$ trailing 0 entries in $\mathbf{u_0}(t), \mathbf{u_1}(t), \mathbf{v_0}(t), \mathbf{v_1}(t)$, respectively.

Before we discuss the relationship between the coefficients, we have some definitions. In the following, we will use $|p|$ to represent the length of a path p, i.e., the number of hops in p.

Definition 11 (Equal-hop Path Set). An equal-hop path set S is a set of paths of the same length. For example $S = \{p_1, p_2, ...\}$, where $|p_1| = |p_2| = ...$, is an equal-hop path set.

Definition 12 (*h*-hop Path Set). An equal-hop path set S is called an h-hop path set if all paths $p \in S$ have the same length $|p| = h$.

Lemma 2. *Consider two equal-hop path sets* $S = \{p_1, p_2, ..., p_q\}$ *and* $S' = \{p'_1, p'_2, ..., p'_r\}$. *Suppose that there is at least one path in* S *that is not in* S' *or there is at least one path in* S' *that is not in* S. *Let* $d \in GF(2^s)$ *be any given fixed value. Let* $a_S(t), t \geq \max_{1 \leq i \leq q}(|p_i|)$, *and* $a_{S'}(t'), t' \geq \max_{1 \leq i \leq r}(|p'_i|)$, *be the coefficients of a non-zero packet after going through* S *and* S', *respectively. Then* $a_S(t)$ *and* $a_{S'}(t')$ *are independently distributed and the probability that* $a_S(t) = da_{S'}(t')$ *is no more than* $1/(2^s - 1)$.

Proof of Lemma 2: Consider a native packet x with no coefficient at the beginning. After going through S and S', the coefficients of the packet will be

$$a_S(t) = \bigoplus_{p \in S} g_p(t), \; a_{S'}(t') = \bigoplus_{p \in S'} g_p(t').$$

$t \geq \max_{1 \leq i \leq q}(|p_i|)$ and $t' \geq \max_{1 \leq i \leq r}(|p'_i|)$ ensure that $g_p(t) \neq 0, p \in S$ and $g_p(t') \neq 0, p \in S'$.

Without loss of generality, suppose there is one path $\tilde{p}$ in S that is not in S'. The coefficient product of $\tilde{p}$, $g_{\tilde{p}}(t)$, is independent of any other coefficient product in $a_S(t)$ and $a_{S'}(t')$. Thus, $a_S(t)$ and $a_{S'}(t')$ are independently distributed. By Lemma 1, $g_{\tilde{p}}(t)$ is non-zero and is uniformly distributed over $GF(2^s)\backslash\{0\}$. The probability for

$$a_S(t) = da_{S'}(t'), \tag{27}$$

i.e., for

$$\begin{aligned} g_{\tilde{p}}(t) &= da_{S'}(t') - a_{S \backslash \{\tilde{p}\}}(t) \\ &= d \bigoplus_{p \in S'} g_p(t') \oplus \bigoplus_{p \in S, p \neq \tilde{p}} g_p(t) \end{aligned}$$

is $1/(2^s - 1)$ when $d \bigoplus_{p \in S'} g_p(t') \oplus \bigoplus_{p \in S, p \neq \tilde{p}} g_p(t) \neq 0$, and 0 when $d \bigoplus_{p \in S'} g_p(t') \oplus \bigoplus_{p \in S, p \neq \tilde{p}} g_p(t) = 0$. Therefore the probability that (27) holds is no more than $1/(2^s - 1)$. ■

Lemma 3. *Consider the equal-hop path sets* $S_0^{+k-1-i_0}$ *and* $T_1^{+k'-1-j_1}$*.The probability that* $a_{S_0^{+k-1-i_0}}(t) \neq 0$ *for any* $t \geq k - 1$ *is no less than* $1 - 1/(2^s - 1)$; *the probability that* $a_{T_1^{+k'-1-j_1}}(t') \neq 0$ *for any* $t' \geq k' - 1$ *is also no less than* $1 - 1/(2^s - 1)$.

Proof of Lemma 3: Recall that i_0 is the length of paths in S_0 and j_1 is the length of paths in T_1. The length of paths in $S_0^{+k-1-i_0}$ is $k-1$, which is the length of the Hamiltonian sub-path $p_0 = 1 - 2 - ... - k$.
Case I: If $S_0^{+k-1-i_0}$ has only one path p_0, then by Lemma 1 $a_{S_0^{+k-1-i_0}}(t) \neq 0$ with probability 1.
Case II: If $S_0^{+k-1-i_0}$ has more than one path, we divide it into two sets $S = \{p_0\}$ and $S' = S_0^{+k-1-i_0} \backslash \{p_0\}$. Then $a_{S_0^{+k-1-i_0}}(t) = a_S + a_{S'}$. By Lemma 2 the probability that $a_S = a_{S'}$ is no more than $1/(2^s - 1)$ when $t \geq k-1$. Therefore $a_{S_0^{+k-1-i_0}}(t) \neq 0$ with probability no less than $1 - 1/(2^s - 1)$.

In conclusion, the probability that $a_{S_0^{+k-1-i_0}}(t) \neq 0$ for any $t \geq k-1$ is no less than $1 - 1/(2^s - 1)$. Similarly we can prove the probability that $a_{T_1^{+k'-1-j_1}}(t') \neq 0$ for any $t' \geq k' - 1$ is also no less than $1 - 1/(2^s - 1)$. ■

Lemma 4. $a_{S_0}(t), a_{S_1}(t)$ *in Eqns. (15)-(16) and* $a_{T_0}(t), a_{T_1}(t)$ *in Eqns. (18)-(19) are non-zero with probability no less than* $1 - 1/(2^s - 1)$.

Proof of Lemma 4: We induct on the coefficients of the newest native packet from $\{x_0(t)\}_{t=0,1,...}$ in the packet received during round t in the following discussion.

When node k has a shortest path of zero hop from the virtual source X_0, i.e., node k is the virtual source X_0, the shortest path is directly from X to node k. It receives $x_0(t)$ within the newest packet and the coefficient of $x_0(t)$ is 1, which is non-zero.

When node k has a shortest path of one hop from X_0, it receives $\alpha_1(t)x_0(t-1)$ within the newest packet, where $\alpha_1(t)$ is the coefficient of X_0 . Since $\alpha_1(t)$ is uniformly distributed over $GF(2^n)\backslash\{0\}$, it is non-zero. Now we assume all shortest paths of i_0 hops from X_0 have non-zero coefficients for $x_0(t-i_0)$.

When node k has a shortest path of $i_0 + 1$ hops from X. Suppose all its adjacent nodes on the shortest paths from X have non-zero coefficients for the newest native packet from $\{x_0(t)\}_{t=0,1,...}$. Consider node l, an adjacent node of node k, that is on some shortest paths from X_0 to k. We focus on one receiving time slot of node k, and two receiving time slots of node l. Let the sets of shortest paths from X_0 to l for $\{x_0(t)\}_{t=0,1,...}$ in the two receiving time slots of a round be $S_{0,l}$ and $S'_{0,l}$. Suppose node l's newest native packets from $\{x_0(t)\}_{t=0,1,...}$ within the two packets received are

$$a_{0,l}(t)x_0(t - i_{0,l}) \text{ and } b_{0,l}(t)x_0(t - j_{0,l}),$$

where

$$a_{0,l}(t) = \bigoplus_{p \in S_{0,l}} g_p(t), \; b_{0,l}(t) = \bigoplus_{p \in S'_{0,l}} g_p(t).$$

and $i_{0,l}, j_{0,l}$ are some non-negative integers with $\min(i_{0,l}, j_{0,l}) = i_0$.

The newest native packet from $\{x_0(t)\}_{t=0,1,...}$ within the packet sent from node l to node k then will be

$$y^l(t) = \begin{cases} \alpha_l(t)[a_{0,l}(t)x_0(t - i_{0,l} - 1)] & \text{if } i_{0,l} < j_{0,l} \\ \alpha_l(t)[(a_{0,l}(t) \oplus b_{0,l}(t))x_0(t - i_{0,l} - 1)] & \text{if } i_{0,l} = j_{0,l} \\ \alpha_l(t)[b_{0,l}(t)x_0(t - j_{0,l} - 1)] & \text{if } i_{0,l} > j_{0,l} \end{cases},$$

Because $a_{0,l}(t)$ and $b_{0,l}(t)$ correspond to different sets of shortest paths in different time slots of a round, and from Lemma 2, $a_{0,l}(t) \neq b_{0,l}(t)$ with probability no less than $1 - 1/(2^s - 1)$, we conclude $a_{0,l}(t) + b_{0,l}(t) \neq 0$ with probability no less than $1 - 1/(2^s - 1)$. By assumption, $a_{0,l}(t)$ is non-zero if $i_{0,l} < j_{0,l}$, because $i_{0,l} = \min(i_{0,l}, j_{0,l}) = i_0$ corresponds to paths of i_0 hops from X_0; similarly $b_{0,j}(t)$ is non-zero if $i_{0,l} > j_{0,l}$; $a_{0,l}(t)$ and $b_{0,j}(t)$ are both non-zero if $i_{0,l} = j_{0,l}$. The probability for the coefficient of $x_0(t - i_0 + 1)$, the newest native packet from $\{x_0(t)\}_{t=0,1,...}$ within $y^l(t)$, to be zero is one of the following:

$$\Pr(\alpha_l(t)a_{0,l}(t)=0)=\Pr(\alpha_l(t)=(a_{0,l}(t))^{-1})=\frac{1}{2^s-1}$$
$$\Pr(\alpha_l(t)(a_{0,l}(t)\oplus b_{0,l}(t))=0)$$
$$=\Pr(\alpha_l(t)=(a_{0,l}(t)\oplus b_{0,l}(t))^{-1})=\frac{1}{2^s-1}$$
$$\Pr(\alpha_l(t)b_{0,l}(t)=0)=\Pr(\alpha_l(t)=(b_{0,l}(t))^{-1})=\frac{1}{2^s-1}.$$

These will be the same as the probability that $a_{S_0}(t)=0$ when there is only one adjacent node that is in the shortest paths from X to k and transmitting.

When there are two adjacent nodes of node k that are in the shortest paths from X to k and transmitting together, let these nodes be denoted by l_0, l_1. Without loss of generality, suppose $i_{0,l_0} < j_{0,l_0}$ and $i_{0,l_1} < j_{0,l_1}$. The received PNC packet will be

$$\begin{aligned}z_0^k(t)=&(\alpha_{l_0}(t)a_{0,l_0}(t)\oplus\alpha_{l_1}(t)a_{0,l_1}(t))x(t-i_0)\\&\oplus f(x_0(t-i_0-1),...,x_0(0))\\&\oplus f(x_1(t-j_1),...,x_1(0))\end{aligned}$$

where i_0 is a non-negative integer. Hence $a_{S_0}(t)=\alpha_{l_0}(t)a_{0,l_0}(t)\oplus\alpha_{l_1}(t)a_{0,l_1}(t)$.

Because $\alpha_{l_0}(t)$ and $\alpha_{l_1}(t)$ are independently uniformly distributed over $GF(2^s)\backslash\{0\}$, the probability for $a_{S_0}(t)=0$ is

$$\begin{aligned}&\Pr(a_{S_0}(t)=0)\\=&\Pr(\alpha_{l_0}(t)=-\frac{\alpha_{l_1}(t)a_{0,l_1}(t)}{a_{0,l_0}(t)})=\frac{1}{2^s-1}.\end{aligned}$$

When there are three adjacent nodes of node k that are in the shortest paths from X to k and transmitting together, let these nodes be denoted by l_0, l_1, l_2. Without loss of generality, suppose $i_{0,l_0} < j_{0,l_0}$ and $i_{0,l_1} < j_{0,l_1}$. The received PNC packet will be

$$\begin{aligned}z_0^k(t)=&(\alpha_{l_0}(t)a_{0,l_0}(t)\oplus\alpha_{l_1}(t)a_{0,l_1}(t)\\&\oplus\alpha_{l_2}(t)a_{0,l_2}(t))x(t-i_0)\\&\oplus f(x_0(t-i_0-1),...,x_0(0))\\&\oplus f(x_1(t-j_1),...,x_1(0))\end{aligned}$$

where i_0 is a non-negative integer. Hence $a_{S_0}(t)=\alpha_{l_0}(t)a_{0,l_0}(t)\oplus\alpha_{l_1}(t)a_{0,l_1}(t)\oplus\alpha_{l_2}(t)a_{0,l_2}(t)$.

Because $\alpha_{l_0}(t)$, $\alpha_{l_1}(t)$ and $\alpha_{l_2}(t)$ are independently uniformly distributed over $GF(2^s)\backslash\{0\}$, the probability for $a_{S_0}(t)=0$ is

$$\begin{aligned}&\Pr(a_{S_0}(t)=0)\\=&\Pr(\alpha_{l_0}(t)=-\frac{\alpha_{l_1}(t)a_{0,l_1}(t)\oplus\alpha_{l_2}(t)a_{0,l_2}(t)}{a_{0,l_0}(t)})=\frac{1}{2^s-1}.\end{aligned}$$

There is no such scenario that there are four adjacent nodes transmit together, because there must be one different color among them. a_{S_0} then will be non-zero with probability no less than $1-1/(2^s-1)$.

By similar arguments, we can show $a_{S_1}, a_{T_0}, a_{T_1}$ are also non-zero with probability no less than $1-1/(2^s-1)$..

■

Lemma 5. *Equations inside (21) are linearly independent with probability at least* $(1-\frac{1}{2^s-1})(1-\frac{2(D+1)}{2^s-1})^{2D-2}$.

Proof of Lemma 5: Consider the first two equations $z_0(k-1)$ and $z_1(k'-1)$ inside (21). The coefficient of $x_0(0)$ in $z_0(k-1)$ is

$$a_{S_0^{+k-1-i_0}}(k-1)=\sum_{p\in S_0^{+k-1-i_0}}g_p(k-1),$$

where $S_0^{+k-1-i_0}$ is the $(k-1)$-hop path set from X_0 to node k, the paths in which have $k-1-i_0$ more hops than a shortest path, which is i_0 hops in length; and the coefficient of $x_1(0)$ in $z_1(k'-1)$ is

$$a_{T_1^{+k'-1-j_1}}(k'-1)=\sum_{p\in T_1^{+k'-1-j_1}}g_p(k'-1),$$

where $T_1^{+k'-1-j_1}$ is the $(k'-1)$-hop path set from X_1 to node k, i.e., the paths that have $k'-1-j_1$ more hops than a shortest path, which is j_1 hops in length. Note that by Lemma 3, with probability no less than $1-1/(2^s-1)$ that $a_{S_0^{+k-1-i_0}}(k-1)$ is non-zero; similarly, with probability no less than $1-1/(2^s-1)$, $a_{T_1^{+k'-1-j_1}}(k'-1)$ is non-zero. In other words, with probability no less than $1-1/(2^s-1)$, $x_0(0)$ will appear in $z_0(k-1)$ and with probability no less than $1-1/(2^s-1)$, $x_1(0)$ will appear in $z_1(k'-1)$.

There are two cases:

1. $x_0(0)$ does not appear in $z_1(k'-1)$ or $x_1(0)$ does not appear in $z_0(k'-1)$. This means that if $x_0(0)$ appears in $z_0(k-1)$ and $x_1(0)$ appears in $z_1(k'-1)$, then $\nexists d\in GF(2^s)$ such that $z_0(k-1)=dz_1(k'-1)$;

2. both $x_0(0)$ and $x_1(0)$ appear in $z_0(k-1)$ and $z_1(k'-1)$: Note that the Hamiltonian sub-paths (defined in Definition 9) are $p_0\in S_0^{+k-1-i_0}$ and $p_1\in T_1^{+k'-1-j_1}$. However, $p_0\notin T_0^{+t-j_0}, 0\le t\le k'-1$, and $p_1\notin S_1^{+t-i_1}, 0\le t\le k-1$. By Lemma 2 the probability that $\exists d\in GF(2^s)$ such that

$$a_{S_0^{+k-1-i_0}}(k-1)=d\cdot(\text{coefficient of } x_0(0) \text{ in } z_1(k'-1))$$

and

$$\text{coefficient of } x_1(0) \text{ in } z_0(k-1)=d\cdot a_{T_1^{+k'-1-j_1}}(k'-1)$$

is no more than $1/(2^s-1)$. To see the above statement, note that we certainly can find a d to satisfy the first equation: i.e., $d=a_{S_0^{+k-1-i_0}}(k-1)\cdot(\text{coefficient of } x_0(0) \text{ in } z_1(k'-1))^{-1}$. However, given this fixed d, the probability of satisfying the second equation is no more than $1/(2^s-1)$ according to Lemma 2. Therefore the probability that $z_0(k-1)=dz_1(k'-1)$, i.e., $z_0(k-1)$ and $z_1(k'-1)$ are linearly dependent, is at most $1/(2^s-1)$. As a consequence, the two equations inside each pair of equations in $\{z_0(t_0), z_1(t_1)\}_{t_0=k-1,t_1=k'-1}$ are linearly independent with probability at least $1-1/(2^s-1)$.

We now proceed with an inductive proof on the linear independence between equations of different pairs. Suppose all equations inside

$$\{z_0(t_0), z_1(t_1)\}_{k-1\le t_0\le k-1+\Delta, k'-1\le t_1\le k'-1+\Delta}, \tag{28}$$

for some Δ, where $0 \le \Delta < D-1$, are linearly independent. Similar to the matrix form of (21) in (22), we represent (28) in matrix form as follows:

$$A(\Delta)\mathbf{x} = \mathbf{z}(\Delta), \tag{29}$$

where

$$A(\Delta) = \begin{bmatrix} \mathbf{u_0}(k-1) & \mathbf{u_1}(k-1) \\ \vdots & \vdots \\ \mathbf{u_0}(k-1+\Delta) & \mathbf{u_1}(k-1+\Delta) \\ \mathbf{v_0}(k'-1) & \mathbf{v_1}(k'-1) \\ \vdots & \vdots \\ \mathbf{v_0}(k'-1+\Delta) & \mathbf{v_1}(k'-1+\Delta) \end{bmatrix} \tag{30}$$

$$\mathbf{x} = \begin{bmatrix} x_0(0) \\ \vdots \\ x_0(D-1) \\ x_1(0) \\ \vdots \\ x_1(D-1) \end{bmatrix} \mathbf{z}(\Delta) = \begin{bmatrix} z_0(k-1) \\ \vdots \\ z_0(k-1+\Delta) \\ z_1(k'-1) \\ \vdots \\ z_1(k'-1+\Delta) \end{bmatrix}, \tag{31}$$

in which $\mathbf{u_0}(t), \mathbf{u_1}(t), \mathbf{v_0}(t), \mathbf{v_1}(t)$ are defined in (25)(26). $A(\Delta)$ is a $2(\Delta+1)\times 2D$ matrix. By assumption all rows in A are linearly independent, i.e., A has full rank $2(\Delta+1)$.

The pair of equations just after the set in (28) are

$$\begin{aligned} z_0(k+\Delta) =& a_{S_0}(k+\Delta)x_0(k+\Delta-i_0) \\ & \oplus a_{S_0^{+1}}(k+\Delta)x_0(k+\Delta-i_0-1) \\ & \oplus ... \oplus a_{S_0^{+k+\Delta-i_0}}(k+\Delta)x_0(0) \\ & \oplus a_{S_1}(k+\Delta)x_1(k+\Delta-i_1) \\ & \oplus a_{S_1^{+1}}(k+\Delta)x_1(k+\Delta-i_1-1) \\ & \oplus ... \oplus a_{S_1^{+k+\Delta-i_1}}(k+\Delta)x_1(0), \end{aligned} \tag{32}$$

$$\begin{aligned} z_1(k'+\Delta) =& a_{T_0}(k'+\Delta)x_0(k'+\Delta-j_0) \\ & \oplus a_{T_0^{+1}}(k'+\Delta)x_0(k'+\Delta-j_0-1) \\ & \oplus ... \oplus a_{T_0^{+\epsilon+\Delta-j_0}}(k'+\Delta)x_0(0) \\ & \oplus a_{T_1}(k'+\Delta)x_1(k'+\Delta-j_1) \\ & \oplus a_{T_1^{+1}}(k'+\Delta)x_1(k'+\Delta-j_1-1) \\ & \oplus ... \oplus a_{T_1^{+k'+\Delta-j_1}}(k'+\Delta)x_1(0), \end{aligned} \tag{33}$$

the coefficients of which are represented by vectors

$$\begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix} \tag{34}$$

and

$$\begin{bmatrix} \mathbf{v_0}(k'+\Delta) & \mathbf{v_1}(k'+\Delta) \end{bmatrix}, \tag{35}$$

respectively. By the same argument as for the previous case of $\Delta = 0$, $z_0(k+\Delta)$ and $z_1(k'+\Delta)$ (and thus $\begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix}$ and $\begin{bmatrix} \mathbf{v_0}(k'+\Delta) & \mathbf{v_1}(k'+\Delta) \end{bmatrix}$) can be shown to be linearly independent with each other. Before deriving the probability that equations (28)$\cup\{z_0(k+\Delta), z_1(k'+\Delta)\}$ are linearly independent, we first evaluate the probability that $\exists \boldsymbol{\beta} \in GF(2^s)^{2(\Delta+1)}$ such that

$$\boldsymbol{\beta}A(\Delta) = \begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix}. \tag{36}$$

That is, we consider $\begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix}$ first without including $\begin{bmatrix} \mathbf{v_0}(k'+\Delta) & \mathbf{v_1}(k'+\Delta) \end{bmatrix}$. If a vector such as $\boldsymbol{\beta}$ exists, then $\begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix}$ is not linearly independent with $A(\Delta)$ (i.e., $z_0(k+\Delta)$ is not linearly independent with (28)).

We use $A(\Delta)_{(r_1,r_2,...;c_1,c_2,...)}$ to denote the submatrix of $A(\Delta)$ that consists of the intersection of rows $r_1, r_2, ...$ and columns $c_1, c_2, ...$. Let

$$\tilde{A} = A(\Delta)_{(1,...,2(\Delta+1);1,...,\Delta+1,D+1,...,D+\Delta+1)},$$

where $\tilde{A}$ is a $2(\Delta+1)\times 2(\Delta+1)$ square matrix that contains the intersection of all rows in $A(\Delta)$ and columns 1 through $\Delta+1$ and columns $D+1$ through $D+\Delta+1$ in $A(\Delta)$.

We use $\mathbf{u}_{(c_1,c_2,...)}$ to denote the subvector of $\mathbf{u}$ that consists of the c_1-th, c_2-th, ... elements of $\mathbf{u}$. Let

$$\tilde{\mathbf{u}} = \begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix}_{(1,...,\Delta+1,D+1,...,D+\Delta+1)}. \tag{37}$$

$\tilde{\mathbf{u}}$ is a vector of length $2(\Delta+1)$ that contains entries 1 through $\Delta+1$ and entries $D+1$ through $D+\Delta+1$ in $\begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix}$. If $\exists \boldsymbol{\beta} \in GF(2^s)^{2(\Delta+1)}$ such that (36) holds, then

$$\boldsymbol{\beta}\tilde{A} = \tilde{\mathbf{u}} \tag{38}$$

holds, too. Now we evaulate the probability of solving $\boldsymbol{\beta}$ from (38).

The first column of $\tilde{A}$ is

$$\tilde{A}_{(1,..,2(\Delta+1);1)} = \begin{bmatrix} a_{S_0^{+k-1-i_0}}(k-1) \\ a_{S_0^{+k-i_0}}(k) \\ \vdots \\ a_{S_0^{+k-1+\Delta-i_0}}(k-1+\Delta) \\ a_{T_0^{+k'-1-j_0}}(k'-1) \\ a_{T_0^{+k'-j_0}}(k') \\ \vdots \\ a_{T_0^{+k'-1+\Delta-j_0}}(k'-1+\Delta) \end{bmatrix}.$$

Recall that one of the two Hamiltonian sub-paths p_0 is in the path set $S_0^{+k-1-i_0}$ but not in $S_0^{+t-i_0}, 0 \le t \le \Delta-1, t \ne k-1$ or $T_0^{+t-j_0}, 0 \le t \le \Delta-1$. By Lemma 2 the first entry $a_{S_0^{+k-1-i_0}}(k-1)$ in $\tilde{A}_{(1,..,2(\Delta+1);1)}$, which is the sole coefficient related to p_0 in this column, is independent of any other entry in the column. In general, the δ-th column of $\tilde{A}$, $1 \le \delta \le \Delta + 1$, is

$$\tilde{A}_{(1,..,2(\Delta+1);\delta)} = \begin{bmatrix} a_{S_0^{+k-\delta-i_0}}(k-1) \\ a_{S_0^{+k-\delta+1-i_0}}(k) \\ \vdots \\ a_{S_0^{+k-\delta+\Delta-i_0}}(k-1+\Delta) \\ a_{T_0^{+k'-\delta-j_0}}(k'-1) \\ a_{T_0^{+k'-\delta+1-j_0}}(k') \\ \vdots \\ a_{T_0^{+k'-\delta+\Delta-j_0}}(k'-1+\Delta) \end{bmatrix},$$

in which by Lemma 2 the δ-th entry $a_{S_0^{+k-1-i_0}}(k-2+\delta)$, which is the sole coefficient related to p_0 in this column, is independent with any one of the other entries. Thus, we conclude that the δ-th entry in column δ, $1 \le \delta \le \Delta + 1$, of $\tilde{A}$ is independent of any other entry in column δ of $\tilde{A}$.
The $(\Delta + 2)$-th column of $\tilde{A}$ is

$$\tilde{A}_{(1,..,2(\Delta+1);\Delta+2)} = \begin{bmatrix} a_{S_1^{+k-1-i_1}}(k-1) \\ a_{S_1^{+k-i_1}}(k) \\ \vdots \\ a_{S_1^{+k-1+\Delta-i_1}}(k-1+\Delta) \\ a_{T_1^{+k'-1-j_1}}(k'-1) \\ a_{T_1^{+k'-j_1}}(k') \\ \vdots \\ a_{T_1^{+k'-1+\Delta-j_1}}(k'-1+\Delta) \end{bmatrix}.$$

Recall that Hamiltonian sub-path p_1 is in the path set $T_1^{+k'-1-j_1}$ but not in $S_1^{+t-i_1}, 0 \le t \le \Delta - 1$ or $T_1^{+t-j_1}, 0 \le t \le \Delta - 1, t \ne k' - 1$. By Lemma 2 the $(\Delta + 2)$-th entry $a_{T_1^{+k'-1-j_1}}(k'-1)$ is independent of any other entry. The δ-th column of $\tilde{A}$, $\Delta + 2 \le \delta \le 2(\Delta + 1)$, is

$$\tilde{A}_{(1,..,2(\Delta+1);\delta)} = \begin{bmatrix} a_{S_1^{+k-\delta+\Delta+1-i_1}}(k-1) \\ a_{S_1^{+k-\delta+\Delta+2-i_1}}(k) \\ \vdots \\ a_{S_1^{+k-\delta+2\Delta+1-i_1}}(k-1+\Delta) \\ a_{T_1^{+k'-\delta+\Delta+1-j_1}}(k'-1) \\ a_{T_1^{+k'-\delta+\Delta+2-j_1}}(k') \\ \vdots \\ a_{T_1^{+k'-\delta+2\Delta+1-j_1}}(k'-1+\Delta) \end{bmatrix},$$

in which by Lemma 2 the δ-th entry $a_{T_1^{+k'-1-j_1}}(k'+\delta-\Delta-3)$ is independent of any other entry. Thus, we conclude that the δ-th entry in column δ, $\Delta + 2 \le \delta \le 2(\Delta + 1)$, of $\tilde{A}$ is independent of any one of the other entries in the same column.

Therefore the diagonal entries of $\tilde{A}$ are independent of any other entry in the same column. After triangularization by elementary row operations, the resulting diagonal entries will be uniformly distributed over $GF(2^s)$. If none of these diagonal entries are 0, the triangularized matrix of $\tilde{A}$ will have full rank. Therefore $\tilde{A}$ has probability $(1 - 1/(2^s - 1))(1 - 1/(2^s - 1))^{2(\Delta+1)} = (1 - 1/(2^s - 1))^{2(\Delta+1)+1}$ to have full rank, i.e., to be invertible.

Since $\tilde{A}$ has probability $(1 - 1/(2^s - 1))^{2(\Delta+1)+1}$ to be invertible, $\boldsymbol{\beta}$ can be solved from (38) by $\boldsymbol{\beta} = \tilde{\mathbf{u}}\tilde{A}^{-1}$ with probability $(1 - 1/(2^s - 1))^{2(\Delta+1)+1}$. Then $\begin{bmatrix} \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \end{bmatrix}$ in (36) is fixed to be $\boldsymbol{\beta}A(\Delta)$. However, $\mathbf{u_0}(k+\Delta)$ contains $a_{S_0^{+k-1-i_0}}(k+\Delta)$, the time-varying random coefficient of $x_0(\Delta+1)$ in $z_0(k+\Delta)$, which is associated with the Hamiltonian sub-path p_0, as its $(\Delta+2)$-th entry. The $(\Delta + 2)$-th column of $A(\Delta)$ is

$$A(\Delta)_{(1,..,2(\Delta+1);\Delta+2)} = \begin{bmatrix} a_{S_0^{+k-\Delta-2-i_0}}(k-1) \\ a_{S_0^{+k-\Delta-1-i_0}}(k) \\ \vdots \\ a_{S_0^{+k-2-i_0}}(k-1+\Delta) \\ a_{T_0^{+k'-\Delta-2-j_0}}(k'-1) \\ a_{T_0^{+k'-\Delta-1-j_0}}(k') \\ \vdots \\ a_{T_0^{+k'-2-j_0}}(k'-1+\Delta) \end{bmatrix},$$

where every entry is independent of $a_{S_0^{+k-1-i_0}}(k+\Delta)$. Hence $a_{S_0^{+k-1-i_0}}(k+\Delta)$ has only $1/(2^s - 1)$ probability to be the value of the $(\Delta + 2)$-th entry in $\boldsymbol{\beta}A(\Delta)$.

On the other hand, $\tilde{A}$ has probability $1 - (1 - 1/(2^s - 1))^{2(\Delta+1)+1}$ not to be invertible. In this case, if $\tilde{u}$ in (38) lies in the image of $\tilde{A}$, then (38) can be satisfied, and there will be more than one $\boldsymbol{\beta}$ that can satisfy (38). If $\tilde{u}$ does not lie in the image of $\tilde{A}$, then (38) cannot be satisfied. For an upper bound, we can simply assume that whenever $\tilde{A}$ is not invertible, (36) can be satisfied. Specifically, overall the probability that $\exists \boldsymbol{\beta} \in GF(2^s)^{2(\Delta+1)}$ such that (36) holds is at most

$$\frac{1}{2^s-1}(1 - \frac{1}{2^s-1})^{2(\Delta+1)+1} + (1 - (1 - \frac{1}{2^s-1})^{2(\Delta+1)+1}).$$

Since

$$1 \ge (1 - \frac{1}{2^s-1})^{2(\Delta+1)+1} \ge 1 - \frac{2(\Delta+1)+1}{2^s-1},$$

we have

$$\begin{aligned} &(\frac{1}{2^s-1})(1 - \frac{1}{2^s-1})^{2(\Delta+1)+1} + (1 - (1 - \frac{1}{2^s-1})^{2(\Delta+1)+1}) \\ \le& \frac{1}{2^s-1} + \frac{(2(\Delta+1)+1)}{2^s-1} \\ =& \frac{2(\Delta+2)}{2^s-1} \\ \le& \frac{2(D+1)}{2^s-1}. \end{aligned}$$

Hence

$$A' = \begin{bmatrix} \mathbf{u_0}(k-1) & \mathbf{u_1}(k-1) \\ \vdots & \vdots \\ \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \\ \mathbf{v_0}(k'-1) & \mathbf{v_1}(k'-1) \\ \vdots & \vdots \\ \mathbf{v_0}(k'-1+\Delta) & \mathbf{v_1}(k'-1+\Delta) \end{bmatrix}$$

has probability at least $1-2(D+1)/(2^s-1)$ to have full rank conditioning on $A(\Delta)$ having full rank. Again conditioning on A' having full rank,

$$A(\Delta+1) = \begin{bmatrix} \mathbf{u_0}(k-1) & \mathbf{u_1}(k-1) \\ \vdots & \vdots \\ \mathbf{u_0}(k+\Delta) & \mathbf{u_1}(k+\Delta) \\ \mathbf{v_0}(k'-1) & \mathbf{v_1}(k'-1) \\ \vdots & \vdots \\ \mathbf{v_0}(k'+\Delta) & \mathbf{v_1}(k'+\Delta) \end{bmatrix}$$

has probability at least $1-2(D+1)/(2^s-1)$ to have full rank. Therefore $A(\Delta+1)$ has full rank (i.e., equations in (28)$\cup\{z_0(k+\Delta), z_1(k'+\Delta)\}$ are linearly independent) with probability at least $(1-2(D+1)/(2^s-1))^2$ conditioning on $A(\Delta)$ having full rank.

Except for $\{z_0(t_0), z_1(t_1)\}_{t_0=k-1, t_1=k'-1}$, the equations of which are linearly independent with probability at least $1-1/(2^s-1)$, all pairs of equations has probability at least $(1-2(D+1)/(2^s-1))^2$ to be linearly independent with the previous pairs of equations. Therefore equations inside (21) are linearly independent with probability at least

$$(1-\frac{1}{2^s-1})(1-\frac{2(D+1)}{2^s-1})^{2D-2}.$$

■

With the above lemmas, we can show that the broadcast throughput upper bound is achievable in grid networks with high probability. This result is presented in the following theorem.

Theorem 2. *The broadcast throughput in grid networks reaches* $2/3$ *with high probability when* s *is of order larger than* $\log D^2$.

Proof of Theorem 2: By Lemma 5, equations inside (21) are linearly independent with probability at least

$$(1-\frac{1}{2^s-1})(1-\frac{2(D+1)}{2^s-1})^{2D-2}. \tag{39}$$

For large s, $(1-\frac{2(D+1)}{2^s-1})^{2D-2}$ can be approximated by

$$\exp(-\frac{2(D+1)(2D-2)}{2^s-1}). \tag{40}$$

Thus, if s is of order larger than $\log D^2$ (e.g., $s=\log D^{2e}$), where $e>1$, the limit of the above probability as $D\to\infty$ is

$$\lim_{D\to\infty}(1-\frac{1}{2^s-1})(1-\frac{2(D+1)}{2^s-1})^{2D-2}=1. \tag{41}$$

Therefore if D is large, at the end of round $(D+\max\{k, MN-k\}-2)$, node k can derive all native packets from X with a high probability. At the end of round $D+MN-2$, all nodes can derive all native packets from X with a high probability. The throughput is

$$\rho = \lim_{D\to\infty}\frac{2D}{3(D+MN-2)} = \frac{2}{3}. \tag{42}$$

■

As a consequence, the broadcast throughput upper bound is achievable with high probability when the field size is of order larger than the logarithm of the number of packets.

V. CONCLUSIONS

In this work, we investigated the relationship between the broadcast throughput upper bound and min-cut in half-duplex broadcast networks. We showed that the theoretical throughput upper bound is $n/(n+1)$ for single-source broadcast, where n is the minimum vertex-cut size of the network. This upper bound is not always achievable in general, but is achievable in grid networks with the help of PNC. A ternary transmission schedule with a three color coloring scheme has been proposed. By constructing a Hamiltonian cycle in the grid network, coloring along the Hamiltonian cycle, and scheduling nodes' transmissions based on the colors, the broadcast throughput is achievable when the field size is of order larger than the logarithm of the number of packets. In the future, we will extend our result and study the achievability of the upper bound in other networks.

APPENDIX

In this appendix, we argue that the broadcast throughput in the network in Fig. 2 cannot reach the upper bound given by Theorem 1. Recall that W_D is the number of time slots (or time window) before all nodes acquire all the D native packets. Let $\mathcal{T}_i$ be the set of time slots during which node i transmits within the W_D time slots; let $\mathcal{R}_i$ be the set of time slots during which node i receives within the W_D time slots.

In order to achieve the the throughput upper bound (i.e., $\rho=2/3$), we need

$$|\mathcal{R}_i| \geq \frac{2}{3}W_D, \forall i \in \{X_0, X_1, 1, 2, 3\}.$$

Since a node cannot transmit and receive at the same time,

$$\begin{aligned} W_D &= |\mathcal{T}_i \cup \mathcal{R}_i| = |\mathcal{T}_i| + |\mathcal{R}_i| - |\mathcal{T}_i \cap \mathcal{R}_i| = |\mathcal{T}_i| + |\mathcal{R}_i| \\ \Rightarrow& |\mathcal{T}_i| = W_D - |\mathcal{R}_i| \leq \frac{1}{3}W_D, \forall i \in \{X_0, X_1, 1, 2, 3\}. \end{aligned} \tag{43}$$

Consider node 1, the throughput for it is

$$\begin{aligned} \rho_1 &\leq |\mathcal{T}_{X_0} \cup \mathcal{T}_{X_1}| = |\mathcal{T}_{X_0}| + |\mathcal{T}_{X_1}| - |\mathcal{T}_{X_0} \cap \mathcal{T}_{X_1}| \\ &\leq \frac{2}{3}W_D - |\mathcal{T}_{X_0} \cap \mathcal{T}_{X_1}| \end{aligned}$$

In order that $\rho_1 \geq \frac{2}{3}W_D$, we need

$$|\mathcal{T}_{X_0} \cap \mathcal{T}_{X_1}| = 0. \tag{44}$$

By focusing on node 2 and node 3, we can apply the same argument to show that

$$|\mathcal{T}_{X_0} \cap \mathcal{T}_3| = 0 \tag{45}$$

$$|\mathcal{T}_{X_1} \cap \mathcal{T}_2| = 0 \tag{46}$$

The throughput of node 2 is

$$\begin{aligned} \rho_2 &\leq |\mathcal{T}_{X_0}| + |\mathcal{T}_3| - |\mathcal{T}_{X_0} \cap \mathcal{T}_2| & (47)\\ &\leq \frac{2}{3}W_D - |\mathcal{T}_{X_0} \cap \mathcal{T}_2| & (48)\\ \Rightarrow &|\mathcal{T}_{X_0} \cap \mathcal{T}_2| = 0 & (49) \end{aligned}$$

if throughput of ρ_2 is to be achieved. (47) is from the half-duplex constraint that when node 2 transmits during the T_2 slots, if X_0 transmits at the same time, no information can be received. (48) is derived from (43). Similarly, we can argue that

$$\begin{aligned} |\mathcal{T}_{X_1} \cap \mathcal{T}_3| = 0 & \quad (50)\\ |\mathcal{T}_2 \cap \mathcal{T}_3| = 0 & \quad (51) \end{aligned}$$

Now, as W_D is the total number of time slots under consideration, we have

$$\begin{aligned} &|\mathcal{T}_{X_0} \cup \mathcal{T}_3 \cup \mathcal{T}_{X_1} \cup \mathcal{T}_2| \leq W_D\\ \Rightarrow &|\mathcal{T}_{X_0} \cup \mathcal{T}_3| + |\mathcal{T}_{X_1} \cup \mathcal{T}_2| - |(\mathcal{T}_{X_0} \cup \mathcal{T}_3) \cap (\mathcal{T}_{X_1} \cup \mathcal{T}_2)| \leq W_D \end{aligned}$$

In order that $\rho_2 = \frac{2}{3}W_D$ and $\rho_3 = \frac{2}{3}W_D$, we need

$$|\mathcal{T}_{X_0} \cup \mathcal{T}_3| \geq \frac{2}{3}W_D$$

$$|\mathcal{T}_{X_1} \cup \mathcal{T}_2| \geq \frac{2}{3}W_D$$

The above are due to the fact that a node can receive information from the transmissions of its neighbors.

$$\begin{aligned} &|(\mathcal{T}_{X_0} \cup \mathcal{T}_3) \cap (\mathcal{T}_{X_1} \cup \mathcal{T}_2)| \geq \frac{1}{3}W_D\\ \Rightarrow &|(\mathcal{T}_{X_0} \cap \mathcal{T}_{X_1}) \cup (\mathcal{T}_{X_0} \cap \mathcal{T}_2) \cup (\mathcal{T}_3 \cap \mathcal{T}_{X_1}) \cup (\mathcal{T}_3 \cup \mathcal{T}_2)| \geq \frac{1}{3}W_D\\ \Rightarrow &|\mathcal{T}_{X_0} \cap \mathcal{T}_{X_1}| + |\mathcal{T}_{X_0} \cap \mathcal{T}_2| + |\mathcal{T}_3 \cap \mathcal{T}_{X_1}| + |\mathcal{T}_3 \cup \mathcal{T}_2| \geq \frac{1}{3}W_D\\ \Rightarrow &|\mathcal{T}_{X_0} \cap \mathcal{T}_2| + |\mathcal{T}_3 \cap \mathcal{T}_{X_1}| + |\mathcal{T}_3 \cup \mathcal{T}_2| \geq \frac{1}{3}W_D \quad (52) \end{aligned}$$

(52) is derived from (44). However, (52) contradicts (49), (50) and (51). Therefore, the throughput upper bound cannot be achieved.

REFERENCES

[1] S. Zhang, S. Liew, and P. Lam, "Hot topic: physical-layer network coding," in *Proceedings of the 12th annual international conference on Mobile computing and networking*. ACM, 2006, pp. 358–365.

[2] B. Bollobas, "Graph theory, an introductory course," 1979.

[3] R. Ahlswede, N. Cai, S. Li, and R. Yeung, "Network information flow," *Information Theory, IEEE Transactions on*, vol. 46, no. 4, pp. 1204–1216, 2000.

[4] P. Gupta and P. R. Kumar, "The capacity of wireless networks," *Information Theory, IEEE Transactions on*, vol. 46, no. 2, pp. 388–404, 2000.

[5] J. Li, C. Blake, D. S. De Couto, H. I. Lee, and R. Morris, "Capacity of ad hoc wireless networks," in *Proceedings of the 7th annual international conference on Mobile computing and networking*. ACM, 2001, pp. 61–69.

[6] S. Wang, Q. Song, X. Wang, and A. Jamalipour, "Distributed MAC protocol supporting physical-layer network coding," *Mobile Computing, IEEE Transactions on*, 2011.

[7] H. Yomo and Y. Maeda, "Distributed MAC protocol for physical layer network coding," in *Wireless Personal Multimedia Communications (WPMC), 2011 14th International Symposium on*. IEEE, 2011, pp. 1–5.

[8] S. Zhang and S. Liew, "Channel coding and decoding in a relay system operated with physical-layer network coding," *Selected Areas in Communications, IEEE Journal on*, vol. 27, no. 5, pp. 788–796, 2009.

[9] S. C. Liew, S. Zhang, and L. Lu, "Physical-layer network coding: Tutorial, survey, and beyond," *Physical Communication*, 2012.